

## **Electric Quiz Board**

- 1. Fill out your template with 12 definitions and 12 words.  
Remember to mix them up!**
- 2. Punch holes in your template.**
- 3. Paperclip the template to your folder.**
- 4. Trace the holes onto your folder.**
- 5. Punch the holes out of your folder.**
- 6. Open the folder up and number the center left holes 1-12 and the  
center right holes A-L.**
- 7. Draw lines connecting the number to the corresponding Letter.  
Use your template as a guide. Word 1 should match the  
definition.**
- 8. Fold 12 pieces of aluminum foil.**
- 9. Place all the foil down that you can that does NOT overlap.  
Secure with tape.**
- 10. Cover with wax paper and add more foil strips. Repeat until all  
12 are taped down.**
- 11. Check by putting a paper clip on the ends of each strip.  
Connect the battery and make sure only one answer lights up  
per word.**
- 12. Close the folder and glue the template on top. ONLY WHEN  
DONE!**
- 13. Attach the brads CAREFULLY through each hole. Make sure  
the prongs are facing up.**
- 14. Add you title and name.**